



Descriptions

The T-1SO1 is a public address pre-amplifier with five balanced MIC inputs, three AUX level inputs and one EMC(priority) level inputs.

Priority muting is achieved via MIC 2 and EMC for overriding music for paging and emergency alarms.

Individual gain controls are provided for MIC and AUX inputs, bass and treble controls are provided for overall tone control.

Features

- * 5-channel MIC input and 3-channel Aux input.
- * With 1-channel EMC input.
- * Independent volume control, MASTER volume control.
- $\ensuremath{^{\star}}$ With compulsive insert and Priority function.
- * MIC balance input interface with phantom power.
- * Individual Gain controls for MIC
- st EMC has priority over all inputs except MIC 2
- $\ensuremath{^*}$ Bass and Treble Tone Controls
- * AC 110V or 230V and DC 24V operation

Specifications

Model	T-1S01
Input Sensitivity &	MIC 2, 3, 4, 5: \pm 2.5mV/2K Ω , Balanced XLR type
Impedance	MIC 2, 3, 4: 5mV/600 Ω , Unbalanced TRS type
	AUX 1, 2, 3: 300mV/10K Ω , Unbalanced RCA type
	EMC: 775mV/47K Ω , Unbalanced TRS type
	MIC 1: \pm 385mV/20K Ω , Balanced MIC 1
Output Sensitivity &	MIX OUT: \pm 775mV/470 Ω , Balanced XLR type
Impedance	REC OUT: 200mV/470 Ω , Unbalanced RCA type
Frequency Response	20Hz-20KHz(\pm 0.5dB)
S/N Ratio	MIC input: 66dB
	AUX input: 80dB
THD	Less than 0.1% at 1KHz, 1/3 rated power
Tone	Bass: \pm 10dB at 100Hz
	Treble: \pm 10dB at 10KHz
Mute	MIC 1 overrides other input signals
	with 0-30dB attenuation
Phantom Power	+48V
Protection	AC fuse
Power Supply	~110V/60Hz or ~230V/50Hz & DC 24V
Dimensions	484x295x44mm
Weight	5Kg



MIC 1 input (for remote paging console T-319) Phone jack Mic 1-3 input Aux1-3 input

48V phantom power for Mic 2-5

XLR Mic 2-5 inputs

Connections

